

# Pulse SENS'O AtEx zone 1



The **Pulse Sens'O AtEx zone 1** remotely reads metering data from water, gas, electricity or heat meters in AtEx zone 1 sensitive areas. **Pulse Sens'O** allows you to make all your mechanical pressure switches communicate with one another in AtEx zone 1 explosive atmospheres. It transforms existing meters into communicating meters via a public or private LoRaWAN® network.

## APPLICATIONS

- In explosive atmospheres, read index values from gas, electricity, water or heat meters with pulse output; load curve monitoring.
- Detection of leaks, fraud and tear off.
- Checking the condition of mechanical pressure switches located in sensitive areas.
- Fast and cost-effective solution that transforms any pulse meter into a communicating meter.

## BENEFITS & FEATURES

- LoRaWAN®, Class A
- Easy to install and use
- 3 pulse inputs or status reports
- SAFT LS17500 Lithium battery on holder
- Differential data compression
- Optional external antenna
- IP55 or IP68
- 10 years of autonomy (data compression mode)

## CERTIFICATION

- RoHS, CE, UKCA
- AteX Zone 1 certification according to marking:
  - Ex II 2 GD
  - Ex ib IIB, IIC T4 Gb
  - Ex ib IIIC T135°C Db
  - -20 ≤ Tamb ≤ +50°C

The **Pulse Sens'O AtEx zone 1** sensor allows remote reading of metering data from the pulse output of water, gas, electricity or energy meters to monitor consumption. **Pulse Sens'O** allows you to make all your mechanical pressure switches in AtEx zone 1 explosive atmosphere communicate with one another and to report changes in status. It transforms existing meters into communicating meters via a public or private LoRaWAN® network.

Three meters can be simultaneously supported by the **Pulse Sens'O AtEx zone 1**, thus allowing a significant reduction in implementation and deployment costs. It can manage tampering detection, flow direction and index.

Installation and commissioning are quick and easy.



*Sensors delivered without WATTECO marking*

The sensor has:

- a switch used for its activation and deactivation,
- 2 LEDs to monitor the configuration and pairing to the network.

Counting data can be stored in the local memory and compressed before being transmitted over the public or private LoRaWAN® network. This reporting technique is particularly suitable for transmitting load curves as it considerably reduces the amount of data transmitted while preserving the autonomy of the sensor.

When powered by a SAFT 3.6V/3600mAh Lithium battery, the autonomy of the sensor is 10 years (in data compression mode) with a configuration that performs one measurement per day and one transmission per day.

Installation, maintenance and operation must be carried out exclusively by a technician qualified for the use of electrical equipment in explosive atmospheres as defined in EN 60079-14.

## THE LARGEST IOT PRODUCTS RANGE FOR YOUR PROJECT

WATTECO is a European leader in the design and manufacture of smart IoT devices to suit all remote reading and data collection solutions.

WATTECO is a LoRa Alliance® member.

### TECHNICAL DATA

RADIO			
Frequency (MHz)	EU: 863-870		
Transmit power (dBm)	+14		
Sensitivity (dBm)	-140		
FIRMWARE			
Protocol	LoRaWAN®, Class A		
Transmission cycles	Configurable from 10 minutes		
Data compression	Yes (differential coding)		
Activation method	ABP or OTAA		
Data encryption	AES128		
INPUTS and intrinsic safety parameters			
U0	6.33V	Ui	25V
I0	33µA	Ii	450mA
P0	23µW	Ci	3.3nF
C0 [IIB]	650µF	Li	~ 0
C0 [IIC]	28µF	Number of entries	3
L0 [IIB]	1H	Frequency (Hz)	0-100
L0 [IIC]	1H		
POWER SUPPLY	Characteristics	Autonomy in the range +10°C to +25°C	
Lithium battery	3.6V / 3600mAh - AtEx Zone 1 certification: battery replacement (only for IP55 version), use only SAFT LS17500 batteries.	10 years with SF12, 1 measurement per day and 1 transmission per day.	
INTERFACE			
LEDs	Configuration and pairing to the network		
Magnetic switch	Reset, ON/OFF		
Cable connection	IP55 – IP68: connection on 6-pin Amphenol connector; see references		
ENCLOSURE	Size (mm)	IP rating	
	92 x 92 x 55.5 (excluding connectors)	IP55 or IP68	
ENVIRONMENT			
Operating temperature (°C)	-20 / +50	Storage temperature (°C)	0 / +30
STANDARDS & REGULATIONS			

Radio Equipment Directive 2014/53/EU, RoHS



### PRODUCT REFERENCES

REFERENCE	IP class	DESCRIPTION
50-70-123	IP55	PULSE SENS'O ATEx ZONE 1IP55
50-70-152	IP68	PULSE SENS'O ATEx ZONE 1IP68
50-70-228	IP55	PULSE SENS'O ATEx ZONE 1IP55 EXTERNAL ANTENNA – NOT INCLUDED
71-70-115	IP67	6-pin Amphenol connector - overmoulded on the 2m cable, end 6pts BINDER plug; shunt3&4 5&6)
71-70-116	IP67	6-pin Amphenol connector - overmoulded on the 2m cable, end JAE plug (for Gazpar)
Others cables and connectors on-demand		

